# **INSTRUCTIONS**

## LARA LED

9286.4.30.30 9286.4.30.31

9286.3.30.30 9286.3.30.31

Please read the instructions before commencing installation and retain for future reference.

#### SPECIFICATIONS:

- Fitting: Metal body with acrylic diffuser.
- Lamp types:

9286.4.30.XX: 12W/230V LED 3000K 9286.3.30.XX: 20W/230V LED 3000K

- Protection against electric shock: CLASS I requires earth connection.
- **Ingress protection:** IP20. Protection against the entry of solid bodies with dimensions more than 12mm.
- Ballast: Includes LED Driver
- Quality/Corrosive rating: Suitable for commercial use, Indoor except in corrosive environments.
- Ambient temperature range: -20° to +50°
- Maximum protected area: 0.20m×0.11m=0.22 m<sup>2</sup>

### INSTALLATION INSTRUCTIONS:

Electrical products can cause death, injury or damage to property. Installation of this product must be carried out by a qualified electrician, in accordance with SANS 10142. On completion of installation, ensure that the Certificate of Compliance is updated.



**CAUTION:** Risk of electric shock

**PLEASE NOTE:** The light source contained on this luminaire shall only be replaced by the manufacturer or the service agent or a similar qualified person.

#### Ensure mains supply is switched off.

- Mark where you would like to install the fitting (Fig. 1)
- Drill holes where you have marked. (Fig.2)
- Insert the expansion plugs and thread the mains cable though the bracket, attach the bracket securely to the wall (Fig.3)
- Connect the terminal block to the main power cable. (Fig. 4)
  Brown(Live) -to Brown or Red
  Blue(Neutral) to Blue or Black
  Yellow/Green(Earth) Green/Copper
- Re-attach the fitting to wall bracket and turn on mains supply. (Fig. 5)

WARNING: Ensure all parts are securely connected and place



